

Catalog Number :

Project Name :

Note :

Date :

Type :

## Description

Square surface-mounted downlights with aluminum die-cast frames, ultra-low profile, perfectly flush with the ceiling.

5 adjustable color temperature;

It is suitable for office, family, hotels, corridors, shopping centers, schools, books and other places.



5"

7"

9"

## Based On Sample Setting. actual Lumens May Vary.

MODEL	SIZE	WATTAGE	5CCT	LUMENS
CL02S-05-10-UC5-D	5inch	10W	2700K	710lm
			3000K	750lm
			3500K	780lm
			4000K	820lm
			5000K	760lm
CL02S-07-15-UC5-D	7inch	15W	2700K	1200lm
			3000K	1220lm
			3500K	1260lm
			4000K	1300lm
			5000K	1250lm
CL02S-09-18-UC5-D	9inch	18W	2700K	1300lm
			3000K	1400lm
			3500K	1440lm
			4000K	1520lm
			5000K	1500lm

## Technical Specification

VOLTAGE	120V
POWER FREQUENCY	60Hz
POWER FACTOR	>0.9
5CCT	2700K   3000K   3500K   4000K   5000K
CRI	90
BEAM ANGLE	120°
MATERIAL	Die casting AL+PS
COLOR	White / Black
LIFESPAN	≥50,000hours
OPERATING TEMP	(-4°F~ 113°F) -20~45°C
DIMMING	Triac Dimmable
RATING	Suitable for Wet Locations
WARRANTY	5 year limited

## Features

Emits evenly, without halo and shadow; Fit 2.75 or 3.5 inch J-Box;  
Support suface mount;

## Stylish And Slim Design

This ultra bright LED Flush Mount is only 0.85 inch thickness.  
The smooth surface is suitable for a variety of decorative styles.

## Dimming

Compatible with 0-10V dimmers to give user a smooth 100%-0% dimming to choose the desired brightness.  
Please check the recommended dimmer list in next page.

## Electrical

This fixture is built with the highest quality 120V drivers, ensuring energy efficiency.

## Listing

ETL Listed.Energy Star.Title24.



Catalog Number: Project Name: Note: Date: Type:

### Die-cast trim

Precision casting, excellent heat dissipation, high corrosion;



### Color temperature optional

2700K-5000K



### Mounting bracket

With multiple apertures, can be installed into any 2.75 or 3.5inch junction box.




■ 2.75" Junction Box installation hole  
■ 3.5" Junction Box installation hole

## Installation Steps

1. Before installing the fixture, ensure the power is off and the J-box is securely installed. Remove the bracket from the fixture by rotating it counterclockwise. Then, use screws to fasten the mounting bracket plate to the J-box (the mounting bracket plate is compatible with 2.75 or 3.5inch J-boxes). See Fig1.



3. Use the CCT switch to select the desired light color. Arrange the wires into the J-box. Align the two rivets on the back of the light fixture with the holes on the wider side of the mounting plate, and then tighten them clockwise until the fixture is secure and parallel to the ceiling. See Fig3, Fig 4.





2. Connect the white wires to white, black wires to black, and copper wire to green wire for grounding. See Fig2.

4. After installation, turn on the power and check if the fixture operates properly. See Figure 4.


## Recommended Dimmer

LUTRON			LEVITON	
CTCL-153P	MSCL-OP153M	MACL-153MA	DVRF-6L	6672
TGCL-153PH-WH	PD-6WCL	DVWCL-153PH	CTCL-150H	RNL06
DVCL-153P	CT-103PR-WH	RCL-153RNL		

## Dimension



0.85"(21.5±2mm)



Specification subject to change without notice